

SYMBOL LEGEND SPRINKLER RISER PENDENT SPRINKLER HEAD/DROP E or N E= EXISTING N= NEW SMOKE DETECTOR E or N
P XXXXXXX E= EXISTING N= NEW P= PHOTOELECTRIC SMOKE - DETECTOR ADDRESS DETECTOR, SMOKE, FOR DUCT REMOTE INDICATOR LAMP AND TEST FAAP FIRE ALARM ANNUNCIATOR PANEL FATC FIRE ALARM TERMINAL CABINET FIRE ALARM CONTROL PANEL NOTIFICATION CIRCUIT POWER BOOSTER PANEL SPEAKER AND STROBE E= EXISTING XXcd (CANDELA RATING) N= NEW W WATTS DOOR HOLDER MAGNETIC RELEASE FIRE ALARM PULL STATION ADDRESSABLE OUTPUT MODULE STROBE LIGHT, WALL MOUNTED XXcd (CANDELA RATING) INDICATES RELOCATION OF DEVICE TO BE REMOVED FIRE/SMOKE DAMPER

LINE LEGEND

Description

VA FORM 08-6231. Oct 1978

REVISIONS

WALL BEING REMOVED

Date

FIRE PROTECTION SYSTEMS GENERAL REQUIREMENTS:

- 1. NOTIFY CONTRACTING OFFICER REPRESENTATIVE (COR) 3 DAYS PRIOR TO PERFORMING WORK ON THE FIRE DETECTION OR SUPPRESSION SYSTEMS.
- PERFORM WORK IN ACCORDANCE WITH APPLICABLE CODES AND STANDARDS. INSTALL ALL EQUIPMENT AS PER MANUFACTURER'S SPECIFICATIONS.
- 3. ALL EQUIPMENT PROCURED FOR THIS PROJECT SHALL BE NEW. EQUIPMENT AND MATERIALS WHICH ARE A COMPONENT OF THE FIRE ALARM OR SUPPRESSION SYSTEM SHALL BE U. L. LISTED OR FACTORY MUTUAL (FM APPROVED).

FIRE ALARM AND DETECTION SYSTEM REQUIREMENTS: (REFERENCE DWG. FA 101 AND FA 102)

- 1. INSTALLATION / MODIFICATIONS OF FIRE ALARM SHALL BE IN ACCORDANCE WITH NFPA 72, NATIONAL FIRE ALARM CODE AND THE VA FIRE PROTECTION DESIGN MANUAL (SIXTH EDITION).
- . ALL DEVICE INSTALLED SHALL BE COMPATIBLE WITH THE FIRE ALARM SYSTEM AND APPROVED BY THE FIRE ALARM SYSTEM MANUFACTURER.
- 8. NEW SPEAKER AND STROBE UNITS WILL BE INSTALLED. CANDELA RATING SHALL BE A MINIMUM AS SPECIFIED IN SECTION 283100.
- 4. LABEL ALL DEVICES WITH ZONE/CIRCUIT/ADDRESS. PAINT ALL JUNCTION BOX COVER PLATES AND LABEL SLC OR NAC OR BOTH.
- 5. SMOKE / FIRE DOOR MAGNETIC HOLDERS WILL REMAIN IN PLACE OR BE MODIFIED TO SUIT THE NEW CONSTRUCTION.
 6. ALL FIRE ALARM WIRING SHALL BE INSTALLED IN RACEWAY SEPARATE FROM ALL OTHER SYSTEMS.
- 7. WIRING SHALL BE THE SIZE AND TYPE AS SPECIFIED IN SECTION 283100
- WIRING FOR LOCAL BUILDING FIRE ALARM SYSTEMS SHALL BE SPECIFIED AS DEFINED IN NFPA 72 AS FOLLOWS:
- A. SIGNALING LINE CIRCUITS (SLC): CLASS B.
- B. NOTIFICATION APPLIANCE CIRCUITS (NAC): CLASS B.C. COMMUNICATIONS BETWEEN BUILDING FIRE ALARM CONTROL UNITS: CLASS X.
- . WIRING INSTALLED IN METAL RACEWAY WITHIN BUILDINGS THAT ARE PROTECTED THROUGHOUT BY SPRINKLERS SHALL BE CONSIDERED TO MEET
- THE REQUIREMENTS FOR PATHWAY SURVIVABILITY LEVEL 2 IN ACCORDANCE WITH NFPA 72 (LATEST EDITION) AS A 2-HOUR PERFORMANCE ALTERNATIVE THAT HAS BEEN APPROVED BY THE AUTHORITY HAVING JURISDICTION AND SHALL BE PERMITTED FOR VOICE COMMUNICATION SYSTEMS IN VA FACILITIES.
- 10. RE-ZONED FIRE AREAS
 A. THE SMOKE BOUNDARY BETWEEN EXISTING ZONE 32 AND ZONE 23 WILL BE COMBINED INTO ONE ZONE. (ZONE 23)
- B. ALL DETECTION AND NOTIFICATION DEVICES SHALL BE REPROGRAMMED TO RESPOND TO ZONE 23 ALARM CONDITIONS. THIS INCLUDES THE SPRINKLER FLOW SWITCHES AND APPROPRIATE DOOR CLOSER RELEASES THAT CURRENTLY SERVE ZONE 32.
- C. CONTRACTOR TO REPROGRAM FIRE ALARM PANEL AS REQUIRED.
- D. SEE DETAIL 2 FOR FIRE ALARM PROGRAMMING MATRIX.
- 11. TESTING AND ACCEPTANCE
 - A. TEST PER CONTRACT SPECIFICATION AND NFPA 72.
 - B. PROVIDE TEST REPORTS PER NFPA 72.
 - C. NOTIFY COR 24 HOURS PRIOR TO PRELIMINARY TESTING

FIRE SPRINKLER SYSTEM REQUIREMENTS: (REFERENCE DWG. FS 101 AND FS 102)

WHEN THIS ITEM IS STAMPED BY A LICENSED PROFESSIONAL

D. NOTIFY COR 3 DAYS PRIOR TO FINAL COMMISSIONING.

- .. INSTALLATION OF SPRINKLER SYSTEMS SHALL BE IN ACCORDANCE WITH NFPA 13, STANDARD FOR THE INSTALLATION OF SPRINKLER SYSTEMS AND THE VA FIRE
- PROTECTION DESIGN MANUAL (SIXTH EDITION).

 2. MATERIALS SHALL BE U.L. LISTED OR FM APPROVED.
- INSTALL FM APPROVED, NEW QUICK RESPONSE SPRINKLER HEADS AS REQUIRED. SPRINKLER HEADS SHOULD MATCH APPEARANCE WITH EXISTING HEADS.
- 4. INSPECT EXISTING PIPING FOR CORROSION PRIOR TO REUSE. IF EXCESSIVE CORROSION IS FOUND REPLACE PIPING.
- POSITION ALL SPRINKLER HEADS IN THE CENTER OF CEILING GRID TILES. USE OF FLEXIBLE SPRINKLER DROPS IS PERMITTED
- ZONE 32 IS BEING ADDED TO ZONE 23. THIS SHOULD NOT AFFECT THE SPRINKLER SUPPLY PIPING IN THAT ALL PIPING IS SUPPLIED FROM THE SAME
- SOURCE. THE FIRE ALARM CONTRACTOR SHALL REPROGRAM THE FIRE ALARM PANEL FOR ZONING PURPOSES WHICH INCLUDES THE SPRINKLER FLOW AND TAMPER SWITCHES. RELABELED ZONE 32 VALVES AND FLOW SWITCHES WITH ZONE 23 LABELS LOCATED IN STAIRWELL 2S3.
- 7. TESTING AND ACCEPTANCE
 A.PER NFPA 13, PARAGRAPH 25.2.1.4 MODIFICATIONS AFFECTING 20 OR FEWER SPRINKLERS SHALL NOT REQUIRE TESTING IN EXCESS OF SYSTEM
 - WORKING PRESSURE. PERFORM 24 HOUR IN-SERVICE LEAK TEST.

 B. AFTER RETURNING THE SYSTEM TO SERVICE PERFORM MAIN DRAIN TEST OF SECTION AFFECTED BY THE MODIFICATION TO ENSURE WATER FLOW
 - IS NOT OBSTRUCTED. THIS CAN BE DONE AT THE FLOOR LEVEL MAIN DRAIN.
 - C. DOCUMENT ALL INSPECTION AND TESTING ON THE CONTRACTORS MATERIAL AND TEST CERTIFICATE.


SPECIAL EQUIPMENT/MATERIALS

ITEM	QTY	DESCRIPTION	MAKE	MODEL
1	1	REMOTE LAMP AND TEST SWITCH	EDWARDS	SD-TRK
2	1	DUCT DETECTOR HOUSING ASSEMBLY	EDWARDS	SIGA-DH
3	1	AIR SAMPLING TUBES, 8"	EDWARDS	62GI-001
4	1	DETECTOR, PHOTO ELECTRIC	EDWARDS	SIGA-PS
5	1	DETECTOR, BASE	EDWARDS	SIGA-SB

Design No. U411

Nonbearing Wall Rating — 2 HR.

* Indicates such products shall bear the UL or cUL Certification Mark for jurisdictions employing the UL or cUL Certification (such as Canada), respectively.




- 1. Floor and Ceiling Runner (Not Shown) Min. 25 MSG galv steel, 1 in. return legs, 2-1/2 in. deep (min), attached to floor and ceiling with fasteners 24 in. OC max.
- 2. **Steel Studs** Min 2-1/2 in. deep, formed of min 25 MSG galv steel max stud spacing 24 in. OC. Studs to be cut 3/4 in. less than assembly height.
- 3. Batts and Blankets* (Optional) Mineral wool or glass fiber batts partially or completely filling stud
- 4. **Gypsum Board*** 5/8 in. thick, outer layer paper, glass mat or vinyl surfaced. (Laminated System) Gypsum board applied vertically in two layers. Inner layer attached to studs with 1 in. long Type S steel screws spaced 8 in. OC along vertical edges, and 12 in. OC in the field and outer layer laminated to inner layer with joint compound, applied with a notched spreader producing continuous beads of compound about 3/8 in. in diameter, spaced not greater than 2 in. OC. Joints of laminated outer layer offset 12 in. from inner layer joints Outer layer gypsum board attached to floor and ceiling runner track with 1-5/8 in. long Type S steel screws spaced 12 in. OC.

Optional, (Direct Attached System), Inner layer attached to studs with 1 in. long Type S steel screws spaced 16 in. OC in the field and along the vertical edges. Outer layer attached to the studs over the inner layer with 1-5/8 in. long Type S steel screws spaced 16 in. OC in the field and along the vertical edges and 12 in. OC to the floor and ceiling runners. Joints of screw-attached outer layer offset from inner layer joints. Joints of outer layer may be taped or untaped.

Nom 3/32 in. thick gypsum veneer plaster may be applied to the entire surface of classified veneer baseboard. Joints reinforced.

FIRE BARRIER REPLACEMENT - AREA B - WEST WALL (U.L.#U411)



VA Fire Protection Design Manual - Fire Alarm System Input Output Matrix


*While NFPA 101 does not require some detectors to notify building occupants, VA requires all smoke detectors, other than duct smoke detectors, to notify building occupants. Only install smoke detectors when required by the Life Safety Code or its references.


** Those doors that are required to be tied to the fire alarm system such as delayed egress and access controlled doors.


a – Do not provide duct detectors in dedicated (100%) exhaust fans, they should continue to run.


2 FIRE ALARM MATRIX
SCALE: NTS


ENGINEER IT IS A VIOLATION OF NEW YORK STATE EDUCATION LAW TITLE VIII ARTICLE 145 SECTION 7209 FOR ANY PERSON UNLESS HE IS ACTING UNDER THE DIRECTION OF A LICENSED **FULLY SPRINKLERED** CONSTRUCTION DOCUMENT PROFESSIONAL ENGINEER TO ALTER THE ITEM IN ANY WAY.
IF AN ITEM BEARING THE SEAL OF A LICENSED PROFESSIONA ENGINEER IS ALTERED THE ALTERING ENGINEER SHALL COMPLY WITH NEW YORK STATE EDUCATION LAW. CONSULTANTS: Drawing Title: Project Title: Project Number: STAMP ARCHITECTS/ENGINEERS: 528A7-14-701 FIRE PROTECTION LEGEND & NOTES **BUSINESS OFFICE RENOVATION** E OF NEW Building Number: S | WApproved: Project Director Location: 800 Irving Avenue Drawing Number: Syracuse, NY 13210 SWBR ARCHITECTS RJR ENGINEERING, P.C. Checked: Drawn: PROFESSIONAL ENGINEERS 309 South Franklin Street Syracuse, NY 13202 Department of CGR Voice: 315.488.5635 www.swbr.com P.O. BOX 344 - 23 Mechanic Street Veterans Affairs Dwg 32 of 56 Springville, New York 14141-0344

























Description

VA FORM 08-6231. Oct 1978

REVISIONS

ELECTRICAL SYMBOLS - POWER PLAN BRANCH CIRCUIT HOMERUN. LINES INDICATE NUMBER OF CIRCUITS, NEUTRAL, AND SWITCH LEG CONDUCTORS. ONE SEPARATE GREEN GROUNDING CONDUCTOR SHALL BE PROVIDED FOR EACH HOMERUN; NOT SHOWN HI VOLTAGE SWITCH ON CONCRETE PAD LOW VOLTAGE SWITCH ON CONCRETE PAD DUAL POWER AND TELECOMMUNICATIONS MANHOLE PANELBOARD CABINET, FLUSH MOUNTED PANELBOARD CABINET, SURFACE MOUNTED

DISCONNECT SWITCH, FUSED DISCONNECT SWITCH, UNFUSED STARTER, COMBINATION WITH DISCONNECT SWITCH STARTER OR MOTOR CONTROLLER VARIABLE FREQUENCY DRIVE ҈тс TIME CLOCK ——D—— POTHEAD → STRESS CONE RECTIFIER, CATHODIC PROTECTION SANITARY VENTILATOR OR FAN COIL UNIT OUTLET CONDUIT TERMINATED 6" [152mm] AFF IN STANDARD BOX FOR EXTENSION TO EQUIPMENT AS DIRECTED. CONDUIT TERMINATED W/COUPLING (FLUSH W/FINISHED FLOOR) FOR EXTENSION TO EQUIPMENT AS DIRECTED. K = KEY OPERATEDF = FUSED SWITCHL = LOCKLM= LOW VOLTAGE MASTER M = MANUAL MOTOR STARTING MC= MOMENTARY CONTACT MP= MOTOR SNAP WITH PILOT LIGHT P = WITH PILOT (THERMAL TYPE) PB= PUSH BUTTON STATION RC= REMOTE CONTROL WP= WEATHER PROOF X = EXPLOSION PROOFMOTION DETECTOR; LETTER INDICATES AS FOLLOWS: C-CEILING D-DESK F-FLUSH H-HIDDEN M-MULLION P-PEDESTAL R-RACK S-SURFACE W-WALL -DUAL TECHNOLOGY IR-INFRARED M-MICROWAVE U-ULTRASONIC X-REQUEST-FOR-EXIT LINE LEGEND

ITEM TO BE DEMOLISHED

EXISTING ITEM TO REMAIN

NEW EMERGENCY POWER CIRCUIT

-X-X-X-X-X-X-X-X-

ELECTRICAL SYMBOLS - POWER PLAN

B LIGHT FIXTURE, RECESSED, 305x1220mm (1'x4'); LETTER INDICATES TYPE. LIGHT FIXTURE, RECESSED, 305x2439mm (1'x8'); LETTER INDICATES TYPE. LIGHT FIXTURE, SURFACE MOUNTED, 610x1220mm (2'x4'); LETTER INDICATES TYPE. B LIGHT FIXTURE, SURFACE MOUNTED, 305x1220mm (1'x4'); LETTER INDICATES TYPE. LIGHT FIXTURE, SURFACE MOUNTED, 305x2439mm (1'x8'); LETTER INDICATES TYPE. LIGHT FIXTURE, EMERGENCY; LETTER INDICATES TYPE. LIGHT FIXTURE, RECESSED, 610x610mm (2'x2'); LETTER INDICATES TYPE. LIGHT FIXTURE, SURFACE MOUNTED, 2'x2' [610x610mm]; LETTER INDICATES TYPE. <u>▼ ▼</u> LIGHT TRACK WITH HEADS AS SHOWN LIGHT FIXTURE, STRIP/INDUSTRIAL FLUORESCENT; LETTER INDICATES TYPE. OH LIGHT FIXTURE, WALL MOUNTED LIGHTING, ONE HEAD EMERGENCY BATTERY POWER LIGHTING, TWO HEAD EMERGENCY BATTERY POWER LIGHTING, THREE HEAD EMERGENCY BATTERY POWER STREET LIGHT WITH BRACKET LIGHT POLE, ONE MAST ARM, ONE LUMINAIRE LIGHT POLE, TWO MAST ARMS, TWO LUMINAIRES LIGHT POLE, POST TOP MOUNT LUMINAIRE LIGHT POLE, ONE LUMINAIRE LIGHT POLE, TWO LUMINAIRES LIGHTING, EXTERIOR BUILDING EXTERIOR FLOOD LIGHT EXIT SIGN, WALL MOUNTED WITH DIRECTIONAL ARROWS AND FACES AS SHOWN EXIT SIGN, CEILING MOUNTED WITH DIRECTIONAL ARROWS AND FACES AS SHOWN LIGHT FIXTURE, BOLLARD

LIGHT FIXTURE, DIRECTIONAL

ELECTRICAL SYMBOLS - LIGHTING PLAN

RECESSED DOWNLIGHT FIXTURE, LETTER INDICATES TYPE.

LIGHT FIXTURE, RECESSED, 610x1220mm (2'x4');

2 = DOUBLE POLE

K = KEY OPERATED

P = WITH PILOT LIGHT

RC= REMOTE CONTROL

WP= WEATHER PROOF

Mo= OCCUPANCY SENSOR

4 = FOUR-WAY

SWITCH (# SUBSCRIPT AS INDICATED BELOW):

SWITCH, CEILING MOUNTED PULL

BLANK = SINGLE POLE

LM= LOW VOLTAGE MASTER

PB= PUSH BUTTON STATION


T = TIMER OPERATED

LETTER INDICATES TYPE.

3 = THREE-WAY

LV= LOW VOLTAGE

D = DIMMER



GENERAL NOTES

- A. ALL FINAL LOCATIONS AND ARRANGEMENTS OF LIGHTING FIXTURES SHALL BE OBTAINED FROM THE ARCHITECTURAL REFLECTED CEILING PLAN. (DWGS A-130, A-131)
- LIGHTING FIXTURES WITH MORE THAN TWO LAMPS SHALL HAVE TWO OUTER LAMPS CONTROLLED WITH ONE SWITCH AND INNER LAMP(S) CONTROLLED BY A SECOND SWITCH.
- EACH BRANCH CIRCUIT HOMERUN SHALL HAVE NO MORE THAN THREE CIRCUITS. EACH BRANCH CIRCUIT HOMERUN SHALL HAVE A SEPARATE GREEN INSULATED EQUIPMENT GROUNDING CONDUCTOR.
- D. MULTI-GANG BACKBOXES FOR DIFFERENT VOLTAGES AND TYPES OF EMERGENCY AND NORMAL BRANCH WIRING DEVICES SHALL HAVE DIVIDERS BETWEEN DEVICES

GENERAL NOTES - DEMOLITION

- A. FOR EXISTING EQUIPMENT, SUCH AS LIGHTING FIXTURES, WIRING DEVICES, CONDUITS, ETC., SHOWN ON PLANS TO BE REMOVED, COMPLETELY CUT/CAP CONDUITS AT THE AREA OF WORK PERIMETER AND REMOVE CONDUIT WITHIN THE WORK AREA, DISCONNECT WIRING AT THE OVERCURRENT PROTECTIVE DEVICE AND REMOVE WIRING COMPLETELY FROM THE ABANDONED CONDUITS.
- DISCONNECT ALL ABANDONED WIRING OF ALL TYPES AT THE OVERCURRENT PROTECTIVE DEVICE. COMPLETELY REMOVE ALL ABANDONED WIRING.
- C. MAINTAIN AND RESTORE, IF INTERRUPTED, ALL CONDUITS AND CONDUCTORS PASSING THROUGH RENOVATED AREAS AND SERVICING UNDISTURBED AREAS.

APPLICABLE CODES

DOCUMENTS PERTINENT TO THE PROJECT ARE AS FOLLOWS:


- NFPA 101 LIFE SAFETY CODE (2015)
- NFPA NATIONAL FIRE CODES WITH THE EXCEPTION OF NFPA 5000 AND NFPA 900 NFPA 10 STANDARD FOR PORTABLE FIRE EXTINGUISHERS

THE APPLICABLE MODEL CODES, STANDARDS AND REFERENCES

- INTERNATIONAL BUILDING CODE (IBC 2012)
- INTERNATIONAL MECHANICAL CODE (IBC 2012)
- ASHRAE STANDARDS
- NATIONAL ELECTRICAL CODE (NEC 2014)
- OCCUPATIONAL, SAFETY AND HEALTH ADMINISTRATION (OSHA) STANDARDS. • VA SEISMIC DESIGN REQUIREMENTS, H-18-8
- ARCHITECTURAL BARRIERS ACT ACCESSIBILITY STANDARDS (ABAAS) INCLUDING VA SUPPLEMENT, BARRIER FREE DESIGN GUIDE
- BUILDING CODE REQUIREMENTS FOR REINFORCED CONCRETE, AMERICAN CONCRETE INSTITUTE AND
- COMMENTARY (ACI 318) MANUAL OF STEEL CONSTRUCTION, LOAD AND RESISTANCE FACTOR DESIGN SPECIFICATIONS FOR STRUCTURALSTEEL


BUILDINGS, AMERICAN INSTITUTE OF STEEL CONSTRUCTION

 ENERGY POLICY ACT OF 2005 (EPACT) VA DIRECTIVES, DESIGN MANUALS, MASTER SPECIFICATIONS, VA NATIONAL CAD STANDARD APPLICATION GUIDE, AND OTHER GUIDANCE ON THE TECHNICAL INFORMATION



ARCHITECTS/ENGINEERS: S|WSWBR ARCHITECTS RJR ENGINEERING, P.C. Date PROFESSIONAL ENGINEERS 309 South Franklin Street Syracuse, NY 13202 Voice: 315.488.5635 www.swbr.com P.O. BOX 344 - 23 Mechanic Street

Springville, New York 14141-0344



1. EXISTING PANEL SCHEDULES SHOWN FOR REFERENCE.
UPDATE TO OMIT REMOVED DEVICES. CIRCUITS
IDENTIFIED AS (NEW) ARE SHOWN ON NEW WORK
PLANS. REMOVED CIRCUITS SHALL BE REIDENTIFIED AS
SPARE. PROVIDE NEW TYPE WRITTEN CIRCUIT
DIRECTORIES WITH TWO SPARE COPIES.

ROOM S103A **VOLTS** 480Y/277V 3P 4W AIC -MOUNTING -BUS AMPS -MAIN BKR 70 FED FROM ECRDP-2 NEUTRAL -LUGS -NOTE -GENERAL LIGHTING
GENERAL LIGHTING
GENERAL LIGHTING
GENERAL LIGHTING
SPARE
(NEW) LIGHTING RM C137,
C138, C154
(NEW) LIGHTING RM C105
(NEW) LIGHTING RM C105 CIRCUIT DESCRIPTION GENERAL LIGHTING GENERAL LIGHTING (NEW) LIGHTING RM C195, C 12 20/1 (NEW) LIGHTING RM C139A SPACE SPACE SPACE SPACE CONN. KVA CALC. KVA CONN. KVA CALC. KVA (125%) CONTINUOUS (125%) HEATING
(100%) NONCONTINUOUS
(50%>10) KITCHEN EQUIP LARGEST MOTOR 0 OTHER MOTORS 0 RECEPTACLES 0 (N/A) NONCOIN/DIVERSE 0 TOTAL KVA BALANCED THREE PHASE AMPS 0 PHASE BALANCE PERCENT: PHASE A 0% PHASE B 0% PHASE C 0%

		- <	· · · · · · · · · · · · · · · · · · ·	1										
ł	RO	<u></u> OM S103) <u> </u>	VOLTS 480Y/277V 3P 4W				/ 3P 4W	N AIC -					
	МО	UNTING	_		BUS	AMPS	_				MAIN I	BKR 60)	
		FROM	ELSDP-	1	NEUTI	RAL –					LUGS	_		
	NO	TE –								•	_			
	CKT #	CKT BKR	LOAD KVA	CIRCUIT DESCR	IPTION			CKT #	CKT BKR	LOAD KVA	CIRCUIT [ESCRIP	TION	
	1	20/1	0	NIGHT LIGHTS			a	2	20/1	0	EXIT SIGN:			
	3 5	20/1 20/1	0 0	SPARE SPARE			b c	4 6	30/3	0	TRANSFOR	MER T-	-LS-2	21
	7	20/1	٠ •	SPARE	~~~	~~~	a	8		li				
	9	20/1	0	(NEW) EMERG CORRIDOR C14		C138,	3	10	20/1	Ō	SPARE			
$\left\{ \left \right. \right. \right.$	11	20/1	0	(NEW) EMERG C123, C135, C	_TG RM 195,	C139,	}	12	20/1	0	SPARE			
4	13	20/1	$\overline{\mathcal{C}}$	CORRIDOR C10 SPARE	~~~	~~) a	14	20/1	0	SPARE			
	15	20/1	0	SPARE			ь	16	20/1	0	SPARE			
	17	20/1	0	SPARE			이	18	20/1	0	SPARE			
	19 21	20/1 20/1	0 0	SPARE SPARE			a b	20 22	20/1 20/1	0 0	SPARE SPARE			
	23	20/1	0	SPARE			c		20/1	0	SPARE			
		20/1	0	SPARE					20/1	0	SPARE			
	27	20/1	0	SPARE			b		20/1	0	SPARE			
	29 31	20/1	0	SPARE SPACE			a	30 32	20/1	0	SPARE SPACE			
	33	_	_	SPACE			Ь	34	_	_	SPACE			
	35	-	-	SPACE			c	36		 	SPACE			
	37	-	-	SPACE				38	-	_	SPACE			
	39 41	_	_	SPACE SPACE			b	40 42	_	_	SPACE			
								_		SPACE				
	LIO	LITING			KVA		^	TI 40	INILIOUIC	_	ONN. KVA	CALC.		
		HTING RGEST MC	0 T OR 0	0	•	(125%) CONTINUOUS (125%) HEATING))	0 0		(125%) (100%)
		HER MOTO		0	•	23 <i>%)</i> 00%)	NONCONTINU				0		(100%)	
		CEPTACLE		0						0	0		(N/A)	
NONCOIN/DIVERSE 0 0									(N/A)					
									_ KVA	•)	0		
		5	SE 544 :	NOT DESCENT	D			ALAI			ASE AMPS	0	• • •	
		PHAS	SE BALA	NCE PERCENT:	PHASE /	A 0%			PHASE	B 0%	F	PHASE (0%	


)_	-1A SFC	$\overline{\top}$	$\overline{\bigcirc \setminus }$	1				
RO	∠ OM S103	<u></u>	VOLTS 208\	<u> </u> (/120	<u> </u>	l	AIC –			
	UNTING		BUS AMPS	•			MAIN BKR -			
	D FROM		NEUTRAL -				LUGS -			
	TE –	PDP-2	NEOTRAL -				LUGS –			
_				<u> </u>	J	1				
CKT #	CKT BKR	LOAD KVA	CIRCUIT DESCRIPTION	CK	T CKT BKR	LOAD KVA	CIRCUIT DESCRIPTION			
1	20/1	0	RECEPT RM S176C	a 2	20/1	0	RECEPT RM S128, S180			
3	20/1	0	RECEPT RM S192, S190	b 4	_ /	0	SPARE			
5	20/1	0	RECEPT RM S199	c 6	20/1	0	RECEPT RM S186, S184B			
7	20/1	0	RECEPT RM S195,S197,S199	a 8	20/1	0	RECEPT RM S180A6, S184A			
9	20/1	0	RECEPT RM S177, S175, S173, S176, S185	b 10	20/1	0	RECEPT RM S190			
11	20/1	0	RECEPT RM S191, S193	c 12	20/1	0	RECEPT RM S195, S197			
13	20/1	0	RECEPT RM S172A, S179		20/1	0	RECEPT RM S191, S193, S195			
15	20/1	0	RECEPT RM S176D, S179	b 16	20/1	0	RECEPT RM S189, S189A			
17	20/1	0	RECEPT RM S172, S176D		20/1	0	RECEPT RM S183, S184, S185, S187			
19	20/1	0	RECEPT RM 176C	a 20	20/1	0	RECEPT RM S180B, S183			
21	20/1	0	RECEPT BEDS 5, 6, 7, 8		20/1	0	SPARE			
23	20/1	0	RECEPT BEDS 5, 6	c 24	20/1	0	SPARE			
25	20/1	0	RECEPT BEDS 7, 8		20/1	0	SPARE			
27	20/1	0	RECEPT BEDS 6, 7, 8	b 28	20/1	0	SPARE			
29	20/1	0	RECEPT RM S174, S176B	c 30	M Y Y Y	Q	SPARE			
31	20/1	0	RECEPT RM S176B	a 32	20/1	0	(NEW) RECEPT RM C195, C196			
33	20/1	0	RECEPT RM S176A	b 34	20/1	0	(NEW) RECEPT RM C195, C196			
35	20/1	0	RECEPT RM S176A	c 36	20/1	О	(NEW) RECEPT RM C195			
37	20/1	0	RECEPT RM S163, S165, S161, S185		20/1	0	(NEW) RECEPT RM C195, C196			
39	20/1	0	ICE MACHINE S161	b 40	20/1	0	(NEW) COPIER RECEPT RM C195			
41	20/1	0	SPARE \	c 42	20/1	0	(NEW) PROJECTION SCREENS			
_			NN. KVA CALC. KVA		 		ONN. KVA CALC. KVA			
LICI	HTING	0		CON	TINUOUS					
	RGEST MO	•	, , , ,	HEA			0 (125%) 0 0 (100%)			
	HER MOTO				CONTINUO		0 (100%)			
	CEPTACLE						0 (N/A)			
		0	3 (33,07 10)		COIN/DIVE		0 (N/A)			
					L KVA		0 0			
				BALA	ANCED TH	REE PH	ASE AMPS 0			
BALANCED THREE PHASE AMPS 0 PHASE BALANCE PERCENT: PHASE A 0% PHASE B 0% PHASE C 0%										


VA FORM 08-6231. Oct 1978


			_P2	2 —	1							
		ROOM S103A MOUNTING - FED FROM LDP-2 NOTE -			VOLTS 480Y/277V 3P 4W BUS AMPS -					AIC — MAIN BKR —		
					NEUTRAL -				LUGS	_		
										_		
		CKT #	CKT BKR	LOAD KVA	CIRCUIT DESCRIPTION		CKT #	CKT BKR	LOAD KVA	CIRCUIT [ESCRIPTIO)N
		1	20/1	0	GENERAL LIGHTING	а	2	20/1	0	CORRIDOR S180	LIGHTING	S150,
		3 5	20/1 20/1	0 0	LIGHTING RM S180, S102 LIGHTING RM S101, C117C C121	b		30/3	0	LIGHTING GENERAL		S102
		7	20/1	0	LIGHTING RM C167, C167A, C167B	a	8			SPARE		
		9	20/1	0	SPARE	b	10	20/1	0	SPARE		
		11	_	0	SPARE	С	12	20/1	0	WATTSTOP	PER PANE	L
	}	13	20/1	0	(NEW) LIGHTING RM C123,	a	14	20/1	0	SPARE		
ŀ	{	15	20/1	0	CORRIDOR C100 (NEW) LIGHTING RM C197, KIOSK ACROSS FROM C139A	b	16	_	_	SPACE		
	ζ	17	20/1	0	(NEW) LIGHTING RM C139) c	18	_	_	SPACE		
	(بور	حسب		SPAGE	a		_	-	SPACE		
		21	_	_	SPACE	b		_	_	SPACE		
		23 25	_	_	SPACE SPACE	c a	24 26	_	_	SPACE SPACE		
1		27	_	_	SPACE	b		_	<u> </u>	SPACE		
)		29	_	_	SPACE	c		_	l_	SPACE		
R		31	_	_	SPACE	a		_	l_	SPACE		
Z		33	_	-	SPACE	b	34	_	 	SPACE		
R		35	-	-	SPACE	С		_	-	SPACE		
K		37	_	_	SPACE		38	_	-	SPACE		
13		39 41		_	SPACE		40 42		_	SPACE		
15	l	41	_	_	SPACE	C	42	_	_	SPACE		
	}				ONN. KVA CALC. KVA				<u>C</u>	ONN. KVA	CALC. K	
1 2			HTING	0	(=)			INUOUS		0	0	(125%)
\mathcal{J}			RGEST MO		()		IEATI			0	0	(100%)
7			HER MOTO		(/			OUNTINUO		0	0	(100%)
		KE	CEPTACLE	:S 0	0 (50%>10)			IEN EQUI		0	0	(N/A)
								OIN/DIVE _ KVA	_	0	0	<u>(</u> N/A)
)										ASE AMPS	0	
			PHAS	SE BALA	ANCE PERCENT: PHASE A 0%		۱۱		B 0%		PHASE C	0%


SEE E-001 FOR GENERAL ELECTRICAL NOTES AND LEGENDS


	WHEN THIS ITEM IS STAMPED BY A LICENSED PROFESSIONAL ENGINEER IT IS A VIOLATION OF NEW YORK STATE EDUCATION LAW TITLE VIII ARTICLE 143 SECTION 7209 FOR ANY PERSON UNLESS ACTING UNDER THE DIRECTION AND PERSON UNLESS ACTING UNDER THE DIRECTION OF A LICENSED PROFESSIONAL ENGINEER TO ALTER THE ITEM IN ANY WAY. IF AN ITEM SEARING THE SEAL OF A LICENSED PROFESSIONAL ENGINEER IS ALTERED THE ALTERING ENGINEER SHALL COMPLY WITH NEW YORK STATE EDUCATION LAW.			FULLY SPRINKLERED	CONSTRUCT	TON DOCUMENT
CONSULTANTS:	STAMP	ARCHITECTS/ENGINEERS:	Drawing Title: ELECTRICAL SO		Project Title: BUSINESS OFFICE RENOVATION	Project Number: 528A7-14-701
	SINTE OF NEW YORK	AR	S W 018			Building Number:
	La L	RJR ENGINEERING, P.C.	Approved: Project Directive States of the st	otor]	Drawing Number: E-602
No. Description Date REVISIONS	O85647 POFESSIONAL FRE	PROFESSIONAL ENGINEERS PROFESSIONAL ENGINEERS 309 Sou	outh Franklin Street Syracuse, NY 13202 /oice: 315.488.5635 www.swbr.com		10/01/1E TDC IFF	Dwg 44 of 56 Department of Veterans Affairs














COMMUNICATION AND ELECTRONIC SAFETY AND SECURITY ABBREVIATIONS MASTER ANTENNA TELEVISION SINGLE-PHASE SINGLE POLE SYSTEM TWO-CONDUCTOR MAXIMUM 3/C THREE-CONDUCTOR MECHANICAL 3PH THREE-PHASE MANHOLE МН 4/C MIN MINIMUM FOUR-CONDUCTOR FOUR-WIRE 4W MOUNT MOUNTED AIR CONDITIONING UNIT MOUNTING ARCHITECT/ENGINEER ALARM ANNUNCIATOR PANEL NOT APPLICABLE ALTERNATING CURRENT OR NATIONAL ELECTRICAL CODE NEUT OR NNEUTRAL ARMORED CABLE ACCESSIBLE NOT IN CONTRACT ADDL ADDITIONAL NS NO SCALE ADJ NOT TO SCALE ADJACENT, ADJOINING ADO AUTOMATIC DOOR OPENER AFC ABOVE FINISHED COUNTER ON CENTER AFF ABOVE FINISHED FLOOR OUTSIDE DIAMETER ABOVE FINISHED GRADE AUTHORITY HAVING JURISDICTION POLE AHJ ALT ALTERNATE PUBLIC ADDRESS AMB OR A AMBIENT PANELBOARD, PULL BOX, OR ARCHITECT PUSHBUTTON AUTOMATIC TRANSFER SWITCH ATS PREFABRICATED BEDSIDE PATIENT AUTO AUTOMATIC UNIT PEDESTAL AUDIO VISUAL PENDANT PF POWER FACTOR BATTERY BARE COPPER РΗ PHASE BD PNL BOARD PANEL BFF PVC POLYVINYL CHLORIDE (PLASTIC) BELOW FINISH FLOOR BLDG PWR POWER BUILDING BPIP BOILER PLANT INSTRUMENTATION REFLECTED CEILING PLAN PANEL REC RECESSED BY PASS RECPT RECEPTACLE CONDUIT RGS RIGID GALVANIZED STEEL CAB CABINET RM ROOM CALC CALCULATE REQUIRED CAP CAPACITY CAT CATALOG SQUARE FOOT (FEET) CATV COMMUNITY ANTENNA TELEVISION SHEET CCR CONTROL CONTACTOR INTERNATIONAL SYSTEM OF UNITS CCTV CLOSED CIRCUIT TELEVISION SPECIFICATION CD CONSTRUCTION DOCUMENTS SURF SURFACE CF SWITCH CONTRACTOR FURNISHED CONTRACTOR FURNISHED/CONTRACTOR INSTALLED TELEPHONE CONTRACTOR FURNISHED/OWNER TWISTED PAIR TWISTED PAIR SHIELDED INSTALLED CONTRACTOR FURNISHED EQUIPMENT TELEPHONE TERMINAL BOARD TELEVISION CEILING CONCRETE MASONRY UNIT COAX COAX CABLE COMM COMMUNICATION UFD UNDERFLOOR DUCT COMPARTMENT UNDERGROUND COMPT UGND CONC CONCRETE UNDERWRITERS LABORATORY CONT CONTINUE UON UNLESS OTHERWISE NOTED CONTR UPS CONTRACTOR UNINTERRUPTIBLE POWER SUPPLY COORDINATE COORD UTIL UTILITY CABLE TELEVISION CTV COPPER VOLT CU CUBIC FEET CU FT WEATHERPROOF CURRENT DECIBEL OR DIRECT BURIAL DIRECT CURRENT DEGREES CELSIUS COMMUNICATION SYMBOLS DEGREES FAHRENHEIT DEMO DEMOLITION DIAG DIAGRAM OUTLET, COMBINATION TELEPHONE/DATA COMMUNICATION DISTR DISTRIBUTION DN DOWN DRSW DOOR SWITCH DWG DRAWING ——FO—— FIBEROPTICS LINE = FO EMPTY CONDUIT EQUIPMENT GROUND TELEPHONE LINE = T ELEVATION ELECTRIC OR ELECTRICAL ---- INTERCOM LINE = I. MINIMUM 3/4" [19mm] CONDUIT. ELEV ELEVATOR **EMER** EMERGENCY ——s— SOUND LINE = S ELECTROMAGNETIC INTERFERENCE EMT ELECTRICAL METALLIC TUBING ----NC---- NURSE CALL LINE = NC. MINIMUM 3/4" [19mm] CONDUIT. **ENCL** ENCLOSURE EPO EMERGENCY POWER OFF RADIO CONDUIT RUN, MINIMUM 3/4" [19mm] CONDUIT. **ESMT** EASEMENT TELECOMMUNICATIONS MANHOLE EXIST EXISTING FLOOR RECEPTACLE, TELEPHONE FLEX FLEXIBLE METALLIC CONDUIT FOUTT TELEPHONE FLOOR OUTLET OUTLET TELEPHONE; LETTER INDICATES AS FOLLOWS: FIRE PROTECTION FP J = JACK TYPE W = WALL TYPEFT FEET OR FOOT FU SW FUSED SWITCH OUTLET DATA ONLY G OR GND GROUND OR GENERATOR OUTLET; LETTER INDICATES AS FOLLOWS: GEN GENERATOR $A = AUDIO \qquad V = VIDEO \qquad I = INTERCOM$ GROUND TERMINAL BOX OUTLET, TELEVISION BLANK = $4 \frac{11}{16}$ " [119mm] MASTER ANTENNA OUTLET BOX HAND-OFF-AUTOMATIC W/BLANK COVER, MTD. 18" [457mm] AFF UNLESS HEIGHT HERTZ OTHERWISE NOTED. C = CAMERA (CCTV SYSTEM), MTD 18" [457mm] AFFINTERMEDIATE METAL CONDUIT M = MONITOR (CTTV SYSTEM).INFRARED TELEPHONE TERMINAL CABINET J-BOX JUNCTION BOX TELEPHONE BACKBOARD (WALL MOUNTED) LINEAR FEET (FOOT) LTNG LIGHTNING LOW VOLTAGE WHEN THIS ITEM IS STAMPED BY A LICENSED PROFESSION. ENGINEER IT IS A VIOLATION OF NEW YORK STATE EDUCATIO LAW TITLE VIII ARTICLE 145 SECTION 7209 FOR ANY PERSON UNLESS HE IS ACTING UNDER THE DIRECTION OF A LICENSE PROFESSIONAL ENGINEER TO ALTER THE ITEM IN ANY WAY IF AN ITEM BEARING THE SEAL OF A LICENSED PROFESSIONAL ENGINEER IS ALTERED THE ALTERING ENGINEER SHALL COMPL WITH NEW YORK STATE EDUCATION LAW. CONSULTANTS: STAMP

REVISIONS

VA FORM 08-6231. Oct 1978

ELECTRONIC SAFETY AND SECURITY SYMBOLS

AUDIO DEVICE; LETTER INDICATES AS FOLLOWS: <u>M=MOUNT</u> C-CEILING D-DESK F-FLUSH H-HIDDEN M-MULLION P-PEDESTAL R-RACK S-SURFACE W-WALL T=TECHNOLOGY/TYPE B-BELL C-CHIME H-HORN K-KLAXON L-LISTEN-IN M-MICROPHONE S-SOUNDER

BI-STATIC BEAM SENSOR; LETTER INDICATES AS FOLLOWS: M = MOUNT

C-CEILING D-DESK F-FLUSH H-HIDDEN M-MULLION P-PEDESTAL R-RACK S-SURFACE W-WALL T=TECHNOLOGY/TYPE

I-INFRARED M-MICROWAVE F=FUNCTION RX-RECEIVE TX-TRANSMIT

S-SPEAKER Z-BUZZER

BIOMETRICS ACCESS CONTROL DEVICE; LETTER INDICATES AS FOLLOWS:

> M = MOUNTC-CEILING D-DESK F-FLUSH H-HIDDEN M-MULLION P-PEDESTAL R-RACK S-SURFACE W-WALL T=TECHNOLOGY/TYPE

H-HAND GEOMETRY F-FINGER PRINT I-EYE IRIS R-EYE RETINA V-VOICE

CARD ACCESS READER; LETTER INDICATES AS FOLLOWS: C-CEILING D-DESK F-FLUSH H-HIDDEN M-MULLION P-PEDESTAL R-RACK S-SURFACE W-WALL

B-BARCODE F-ELEVATOR FLOOR CALL H-ELEVATOR HALL CALL M-MAG STRIP P-PROXIMITY S-SMART CARD T-TOKEN

CARD READER WITH KEYPAD; LETTER INDICATES AS FOLLOWS: C-CEILING D-DESK F-FLUSH H-HIDDEN M-MULLION P-PEDESTAL R-RACK S-SURFACE W-WALL

VIDEO CAMERA WITH LENS

ELECTRONIC LOCK; LETTER INDICATES AS FOLLOWS:

C-CEILING D-DESK F-FLUSH H-HIDDEN M-MULLION P-PEDESTAL R-RACK S-SURFACE W-WALL T=TECHNOLOGY/TYPE D-DEADBOLT H-HYBRID L-LATCH SET M-MAGNETIC S-STRIKE

MOTION DETECTOR; LETTER INDICATES AS FOLLOWS:

M=MOUNT C-CEILING D-DESK F-FLUSH H-HIDDEN M-MULLION P-PEDESTAL R-RACK S-SURFACE W-WALL T=TECHNOLOGY/TYPE

D-DUAL TECHNOLOGY IR-INFRARED M-MICROWAVE U-ULTRASONIC X-REQUEST-FOR-EXIT

PUSH BUTTON; LETTER INDICATES AS FOLLOWS:

<u>M=MOUNT</u> C-CEILING D-DESK F-FLUSH H-HIDDEN M-MULLION P-PEDESTAL R-RACK S-SURFACE W-WALL

T=TECHNOLOGY/TYPE B-BELL PUSH D-DURESS P-PANIC R-DOOR RELEASE X-REQUEST-FOR-EXIT

D-DELAYED EGRESS E-ELECTRIFIED M-MECHANICAL

EXIT DEVICE; LETTER INDICATES AS FOLLOWS: T=TECHNOLOGY/TYPE

X-HIGH SECURITY

GENERAL NOTES

FUTURE INSTALLATION.

1. VERIFY BOX LOCATION WITH COR PRIOR TO ROUGHING IN THE INSTALLATION.

2. ALL WALL MOUNTED BACK BOXES TO A MINIMUM OF 18 INCHES ABOVE THE FINISHED FLOOR UNLESS OTHERWISE SPECIFIED IN THE KEY NOTES.

3. ALL DATA AND PHONE LINES SHALL BE INSTALLED IN A MINIMUM 1" EMT CONDUIT RUN VERTICALLY IN THE WALLS AND STUBBING ABOVE THE CEILING BY AT LEAST 1 INCH. INSTALL WITH A PULL STRING TO SIMPLIFY

4. ALL WIRING FOR COMMUNICATION DEVICES SHALL BE INSTALLED WITH A PULL STRING TO SIMPLIFY FUTURE INSTALLATION.

5. USE EXISTING TIE-IN POINTS FOR WIRE TERMINATION. 6. ALL WIRING ABOVE SUSPENDED CEILING WILL BE SUSPENDED USING APPROVED WIRE HANGERS OR BASKET CABLE TRAYS.

7. OUTLET BOXES SHALL BE THE SAME MINIMUM SIZE AS NEC STANDARD 6 IN x 6 IN x 2.5 IN THAT COULD CONTAIN DUAL DUPLEX ELECTRICAL OUTLETS.

OUTLET BOXES SHALL BE EQUIPPED WITH FULL COVERED WALL FACEPLATES THAT SHALL COVER THE ENTIRE BOX WITHOUT TRIM RINGS ADDED, AND SHALL EMPLOY TWO EACH MODULAR CATEGORY 6 (OR BETTER) RJ-45/11 JACKS FOR VOICE, AND TWO EACH MODULAR CATEGORY 6 (OR BETTER) RJ-45 JACKS FOR DATA. THE BOX SHALL ALSO PROVIDE SPACE FOR THE ADDITION OF ONE MODULAR STAINLESS STEEL (AT&T-ST) FIBER-OPTIC JACK AND ONE BNC.

9. PLENUM/CMP RATED WIRE OR CABLE SHALL BE PROVIDED IN ALL AIR-HANDLING PLENUM LOCATIONS. NON-PLENUM/CM WIRE OR CABLE MAY BE PROVIDED IN ALL OTHER AREAS.

APPLICABLE CODES

THE APPLICABLE MODEL CODES, STANDARDS AND REFERENCES DOCUMENTS PERTINENT TO THE PROJECT ARE AS FOLLOWS:

NFPA 101 LIFE SAFETY CODE (2015)

 NFPA NATIONAL FIRE CODES WITH THE EXCEPTION OF NFPA 5000 AND NFPA 900

NFPA 10 STANDARD FOR PORTABLE FIRE EXTINGUISHERS

INTERNATIONAL BUILDING CODE (IBC 2012)

 INTERNATIONAL MECHANICAL CODE (IBC 2012) ASHRAE STANDARDS

 NATIONAL ELECTRICAL CODE (NEC 2014) OCCUPATIONAL, SAFETY AND HEALTH ADMINISTRATION

(OSHA) STANDARDS. VA SEISMIC DESIGN REQUIREMENTS, H-18-8 ARCHITECTURAL BARRIERS ACT ACCESSIBILITY STANDARDS

(ABAAS) INCLUDING VA SUPPLEMENT, BARRIER FREE DESIGN GUIDE

 BUILDING CODE REQUIREMENTS FOR REINFORCED CONCRETE, AMERICAN CONCRETE INSTITUTE AND COMMENTARY (ACI 318)

 MANUAL OF STEEL CONSTRUCTION, LOAD AND RESISTANCE FACTOR DESIGN SPECIFICATIONS FOR STRUCTURALSTEEL BUILDINGS, AMERICAN INSTITUTE OF STEEL CONSTRUCTION


• ENERGY POLICY ACT OF 2005 (EPACT) VA DIRECTIVES, DESIGN MANUALS, MASTER SPECIFICATIONS, VA NATIONAL CAD STANDARD APPLICATION GUIDE, AND OTHER GUIDANCE ON THE TECHNICAL INFORMATION


CONSTRUCTION DOCUMENT FULLY SPRINKLERED Project Title: Drawing Title: Project Number: COMMUNICATIONS, DATA, & SECURITY **BUSINESS OFFICE RENOVATION** 528A7-14-701 GENERAL NOTES AND LEGEND Building Number: Location: 800 Irving Ave Approved: Project Director Drawing Number: Syracuse, NY 13210 Checked: ||Drawn: Department of TRG Veterans Affairs


Dwg 51 of 5


ARCHITECTS/ENGINEERS: S|WSWBR ARCHITECTS RJR ENGINEERING, P.C. PROFESSIONAL ENGINEERS 309 South Franklin Street Syracuse, NY 13202 Voice: 315.488.5635 www.swbr.com P.O. BOX 344 - 23 Mechanic Street


Springville, New York 14141-0344












Description

VA FORM 08-6231. Oct 1978

REVISIONS

Date



TYPICAL CARD READER 1 DOOR ACCESS RISER SCALE: NONE

RJR ENGINEERING, P.C.

PROFESSIONAL ENGINEERS

P.O. BOX 344 - 23 Mechanic Street Springville, New York 14141-0344

